



## USB to 2 Port Serial Converter

No.: 42889

Connects 2 serial devices to a USB Type A computer

### Description

- Connects two standard serial devices via USB Type A
- Two 9 Way D Male to 1x USB A Male connector
- Plug & Play - USB bus-powered with no external power supply required
- Compatible with Windows and Mac Operating Systems
- 2 year warranty

The Lindy USB to 2 Port Serial Converter allows the user to easily connect two peripheral devices featuring 9 Way Serial RS232 simultaneously to a USB Type A port. With both USB Type A and serial connectors, this device is a perfect solution for connecting legacy RS232 equipment such as barcode scanners and industrial devices to notebooks and Macbooks, in retail, IT and digital signage scenarios.

This converter is compatible with both Windows and Mac operating systems and as it is USB bus-powered, it can be installed quickly and simply with no need for additional power supplies.

### Technical details

#### Specifications

- Interface: USB to 2 x RS232 Serial
- Interface Standard: USB 1.1, RS232
- Supported Bandwidth: 12Mbps, > 230kbps
- Chipset: FTDI
- Compatibility: USB Type A equipped computers
- Power Delivery: -
- Special Features: -

#### Connectors

- Inputs: 1 x USB Type A (Male)
- Outputs: 2 x RS232 9 way (Male)
- Power: Bus-powered

#### Physical Properties

- Dimensions WxDxH:
  - 70x70x23mm [2.76x2.76x0.91in] / RS232
  - 14x39x8mm [0.55x1.54x0.31in] / USB
- Cable Length: 60mm [2.36in]
- Housing Material: Plastic
- Net Weight: 0.08kg [0.18lb]
- Operating Temperature: 0°C - 50°C [32°F -122°F]

- Storage Temperature: -20°C - 70°C (-4°F - 158°F)
- Humidity: 0 - 80% RH (non-condensing)
- Power Requirements: -
- Colour: Silver

#### **Miscellaneous**

- Packaging Type: Polybag
- Packaging Dimensions: 174x194mm (6.85x7.64in)
- Gross Weight: 0.09kg (0.2lb)
- Warranty (Years): 2
- Certificated: CE, FCC, RoHS & REACH

#### **Package Contents**

- USB to 2 Port Serial Converter

#### **Purchasing information**

- No.: 42889
- EAN: 4002888428897

© LINDY 2021