



## 2 Port DVI-D Single Link, USB 2.0 & Audio Cable KVM Switch

No.: 42341

Switch between 2 DVI equipped PCs from one keyboard, mouse and monitor

### Description

- Controls two DVI equipped PCs from a single keyboard, mouse and monitor
- Switch via the unit's push buttons, software or keyboard hot keys
- Supports DVI-D single link signals, up to 1920x1200
- Integrated cables for quick, hassle-free installation
- 2 year warranty

A KVM switch allows an operator to conveniently control and manage multiple devices, such as PCs and servers, from a single keyboard, mouse and display console.

The Lindy 2 Port DVI-D Single Link, USB 2.0 & Audio KVM Switch is a compact solution for providing access and control over two DVI equipped PCs from a single keyboard, mouse and monitor set. With integrated cables, this switch can be easily connected directly to the system, with no need to purchase additional cables, saving time and money on installation.

Support for single link resolutions up to 1920x1200, for HDMI monitors, graphics cards, notebooks or PCs with higher resolutions, Deep Colour & 3D, use the Lindy HDMI KVM Switch instead. The audio output port on the main unit allows users to connect headphones or speakers to add immersive 2CH audio and a microphone. Keyboards and mice can be connected to dedicated USB ports on the main unit, other peripherals or hubs are not supported.

The KVM switch features multiple switching options including push buttons on the unit alongside hotkey and software switching to provide simple, reliable control for the user, great for both professional and first time users.

Please note: Software control & hotkey switching are not currently compatible with devices supporting macOS 10.15. This is due to an incompatibility between macOS 10.15 and 32-bit software.

### Technical details

#### Specifications

- AV Interface: DVI-D
- Console Interfaces: USB
- Interface Standard: DVI-D (Single Link), USB 2.0
- Maximum Resolution: 1920x1200@60Hz

- HDCP Support: 1.4
- Supported Audio: Analogue Stereo
- Separate Audio Ports: 2 x 3.5mm (Female)
- Serial Interface: -
- Console Number: 1
- Max Number PC/Server: 2
- Cascadable: -
- Switching Method: Port Buttons, Hotkey Switching & Software
- 19" Rack Mountable: -
- Special Features: Active LED Indicators

#### Connectors

- Console Interfaces: DVI (Female), USB 2.0 Type A (Female), 2 x 3.5mm (Female)
- PC/Server Interfaces: 2 x DVI-D (Male), USB 2.0 Type A (Male), 2 x 3.5mm (Male) Integrated Cables
- Other Interfaces: -
- Power: -

#### Physical Properties

- Dimensions WxDxH: 87x25x58.78mm (3.43x0.98x2.31in) Cable length 0.9m (2.95ft)
- Housing Material: Plastic
- Net Weight: 0.46kg (1.01lb)
- Operating Temperature: 0°C - 50°C (32°F - 122°F)
- Storage Temperature: -20°C - 60°C (-4°F - 140°F)
- Humidity: 0~90% RH (non-condensing)
- Power Requirements: Via USB
- Colour: Black

#### Miscellaneous

- Packaging Type: Carton box
- Packaging Dimensions: 160x60x210mm (6.3x2.36x8.27in)
- Gross Weight: 0.6kg (1.32lb)
- Warranty (Years): 2
- Certificated: CE, FCC, RoHS, REACH & California Proposition 65

#### Package Contents

- DVI KVM switch
- Lindy Manual

#### Purchasing Information

- No.: 42341
- EAN: 4002888423410